



# Azur 851N IR Remote Control Codes

v1.0

*All codes are RC-5.  
System code 24 or 27 (switchable within 851N Settings menu)*

Function	Decimal command code
More	09
Home	12
Up	13
Filter	14
Left	16
Select	17
Right	18
Down	19
Random	20
Repeat	21
Return	22
Skip Left	23
Play/Pause	24
Skip Right	25
Stop	27
Info	28
Bluetooth	31
USB Audio	32
D3	33
D4	34
D1	35
D2	36
D5	37
Queue	42
LCD Off	49
LCD Dim	50
LCD Bright	51
Preset 1	57
Preset 2	58
Preset 3	59
Preset 4	60



The following Power commands are supported

*System code 24*

Function	Decimal command code
Power	02
Standby	03
Power On	102
Power Off	103

The following codes are also supported when the 851N is in Digital Pre-amp mode

*System code 16*

Function	Decimal command code
Mute toggle	13
Vol +	16
Vol -	17

Information in this document has been carefully checked for accuracy; however, Cambridge Audio's policy is one of continuous improvement, therefore design and specifications are subject to change without prior notice. If you notice any errors please feel free to contact us at: <http://support.cambridgeaudio.com/>

This document contains proprietary information protected by copyright. All rights are reserved. No part of this document may be reproduced by any mechanical, electronic or other means, in any form, without prior written permission of the manufacturer.

© Copyright Cambridge Audio Ltd 2015